



### Q Series Karaoke Speaker



Q series loudspeaker three way full range design. Uses 8"-12"x1 high sensitivity LF driver and 3"x2 MF and HF driver. High definition and efficiency return function. It is perfect for multi-functional room KTV.

#### SPECIFICATIONS

##### 8Q Karaoke loudspeaker

Driver	: LF8"x1 HF3"x2 MF:3"x2
Impedance	: 8 ohm
Power	: 150W
Frequency	: 55hz-16khz
Size(HxWxD)	: 250*485*295mm
Long-term SPL	: 115db
Sensitivity	: 96db

##### 10Q Karaoke loudspeaker

Driver	: LF10"x1 HF3"x2 MF:3"x2
Impedance	: 8 ohm
Power	: 180W
Frequency	: 45hz-16khz
Sensitivity	: 98db
Long-term SPL	: 117db
Size(HxWxD)	: 305*515*330mm

##### 12Q Karaoke loudspeaker

Driver	: LF12"x1 HF3"x2 MF:3"x2
Impedance	: 8 ohm
Power	: 230W
Frequency	: 45hz-18khz
Sensitivity	: 99db
Long-term SPL	: 120db
Size(HxWxD)	: 355*565*335mm



Specifications are subject to change without prior notice for future improvement